



CD-2000

A Brain Transplant for your CD-80®



The CD-2000 is a professional retrofit electronics package designed specifically for any vintage of Strand CD80® dimmer rack. This full-featured, state-of-the-art unit converts dual DMX inputs with protocol manager to 96 PWM and 128 DMX channels of output.

Standard software includes architectural features such as DMX snapshots, scene storage, time clock, power management, auto scheduling, dimmer rack diagnostics and much more. Designed to install in minutes, this product is the proven and much talked about solution for CD80® dimmer racks.

The CD-2000 makes expensive replacement of antiquated dimming systems completely unnecessary. At a fraction of installed replacement cost and downtime, this engineered long-term solution puts state-of-the-art dimming technology at your fingertips!

- ✦ The engineered solution for CD80® dimmer racks. Replaces the old electronic card cage with new state-of-the-art control electronics.
- ✦ Upgrades any vintage of rack in minutes.
- ✦ A full-featured cost-effective solution for rack owners requiring a long-term, user-friendly front end for their dimmer rig.
- ✦ Compatible with O.E.M. dimmer rack wiring for fast easy installation.
- ✦ Dual opto-isolated DMX inputs with built in protocol manager.
- ✦ 16 analog inputs and an infrared LED link for wireless printouts of programmed data.
- ✦ Modular design with only two "plugable" modules.
- ✦ Site programmable via a user-friendly, intuitive and self-prompting menu structure. No laptop computer or special software is required!
- ✦ Powerful architectural software features include DMX snapshots, power management and over 40 more.
- ✦ Auxiliary 128 channel DMX output for incorporation of peripheral DMX devices into the system's architectural control.
- ✦ Supports all Johnson Systems control stations.
- ✦ Networking between multiple CD-2000's allows for integrated control of multi-rack installations.
- ✦ Up to 10 year product warranty available!



JOHNSON SYSTEMS INC.

"PROGRESSIVE ALTERNATIVES IN LIGHTING CONTROL"

1923 Highfield Crescent S.E.
Calgary, Alberta, Canada T2G 5M1
tel: 403.287.8003
fax: 403.287.9003
e-mail: info@johnsonsystems.com
website: www.johnsonsystems.com

MANUFACTURER MEMBER

ESTA



ENTERTAINMENT SERVICES &
TECHNOLOGY ASSOCIATION

CD-2000 SPECIFICATIONS

1.0 CD-2000 - GENERAL

CD-2000 is a direct retrofit assembly kit specifically designed for facilities with an existing Strand CD80® dimming system requiring a reliable front-end control unit. This product will upgrade existing dimmer installations to current dimming technology with options equaling or exceeding those of most new dimming systems. The CD-2000 has been engineered as a long-term solution for facilities requiring a powerful yet user-friendly and cost-effective front end. CD-2000 carries an industry leading 3-year warranty. As a direct replacement product, the CD-2000 is pin to pin compatible with OEM factory wiring for ease of installation. Facilities can upgrade to this new technology in minutes. The CD-2000 is ETL approved and complies fully with UL 508 and CSA 22.2 safety approvals. Engineered with both the installer and end-user in mind, the CD-2000 incorporates the following features:

- 1.1 A user friendly software package allowing ease of programming and configuration changes. A self-prompting menu shall make a users manual virtually unnecessary.
- 1.2 Modular design of the unit shall make any future service requirements fast and easy with no requirement for an on-site service call. The CD-2000 shall have only two pluggable modules. The PSR (Power Supply & Ramp) module shall contain power supplies, phase detect circuitry, panic function, and DMX input/output opto-isolation. The ECU (Electronic Control Unit) module shall contain the main processor and all ancillary control electronics for the dimmer rack.
- 1.3 Dimmer control outputs shall be designed for precise and reliable control of the existing CD80® dimmer modules. It shall never be necessary to adjust ramp circuits for proper dimmer output.
- 1.4 The CD-2000 shall accept dual independent DMX 512-A digital data protocol inputs allowing industry wide compatibility with most control consoles. Primary DMX input and DMX through connectors shall be provided on both the backplane of each unit as well as on the face panel of the PSR module. A second DMX input port shall be located on the rear of the unit only. Both DMX inputs shall be independently opto-isolated from all other control circuitry, as well as from the DMX output ports.
- 1.5 An on-board protocol manager shall be provided for facilities operating back-up consoles and/or second DMX sources.
- 1.6 An auxiliary 128 channel DMX output shall allow control of other DMX receivers thereby allowing the CD-2000 to create the architectural "front-end" control system for inclusion of secondary houselight dimmer racks, demultiplexers, relay panels, etc.
- 1.7 An infrared LED link shall be provided on the ECU face panel. This interface will permit hard copy printouts of all programmed data via an optional hand held infrared printer.
- 1.8 An illuminated ON/OFF disconnect breaker shall be provided on the face of CD-2000. This shall facilitate ease of power up/down of rack the electronics on an individual basis.
- 1.9 A separate long-life air filter and grill assembly shall provide a means for easy and routine maintenance.
- 1.10 A set of three (3) high output, low noise fans shall provide maximum cooling of the dimmer rack by concentration of airflow directly upwards on the vertical columns of dimmer module heatsinks.

2.0 ELECTRONIC MODULES

Control electronics shall be contained in two plug-in trays and shall provide the following features:

- 2.1 The control electronics shall be capable of controlling up to 96 dimmers in the CD80® dimmer cabinet. In addition, the control electronics shall be capable of controlling up to 32 additional dimmers/devices by means of an auxiliary 128-channel DMX512 output.
- 2.2 The data input ports shall accept two independent sources of DMX512 data protocol simultaneously from the system control console(s) or architectural control unit(s).
- 2.3 It shall be possible to assign (patch) any dimmer control signal to any module position in the cabinet, thereby allowing dimmer modules of any rating to be used in the same cabinet.
- 2.4 The ECU module shall be capable of memorizing a minimum of 18 presets with individual time fade for recall from Johnson Systems CS-2809 System Management Control (SMC) stations. These presets be DMX "snap-shots" available for instant playback in the event of control console failure. These presets shall be automatically locked out when the system control console is on to prevent accidental access. It shall be possible to "back up" all system configuration data. All such data shall be protected from power failure by EEROM for a minimum of 100 years.
- 2.5 A time-of-day clock shall be incorporated into the ECU module electronics. Scheduled preset times shall be programmable to permit system automation through automatically scheduled preset events. The clock shall be protected from power failure by a lithium cell with minimum 10-year life.
- 2.6 The ECU module shall accept up to 16 analog inputs (0-10 volt DC) with the ability to be assigned to any of the 128 dimmer outputs in the system (2048 possible assignments). The analog inputs shall function in a pile-on or HTP mode with the console control DMX signal.
- 2.7 Each individual dimmer in the dimmer cabinet shall be capable of being assigned one of four dimmer curves; incandescent square law, fluorescent, linear, or non-dim.

- 2.8 The face of the ECU module shall include an alphanumeric LED display and momentary push buttons for function select and parameter setting. All system configuration data shall be stored in non-volatile RAM with full redundancy back up to 100 year EEROM.
- 2.9 The following functions shall be programmable:
 1. Mode select (Master or Slave).
 2. DMX address select, in unit dimmer increments.
 3. Control signal to dimmer assignment (channel/dimmer patch).
 4. Analog input patch of 16 x 128 (2048 total).
 5. Preset record enable/disable.
 6. Preset fade times of 0 to 99 seconds (separate time for each preset).
 7. Preset recall (for programming changes).
 8. Room lock out with 4 digit PIN access code.
 9. Dimmer curve assignment (incandescent, fluorescent, linear, or non-dim).
 10. Time-of-day clock set.
 11. Automatic scheduling (Preset "ON" and "OFF" time-of-day).
 12. Test increments (percent or hex value).
 13. System defaults (for quick programming).
 14. DMX input status hold (0-99 minutes).
 15. After hours preset time out (0-99 minutes).
 16. Assignable "Tour" preset (0-99 minutes).
 17. Edit capture (DMX level or instant channel capture).
 18. Backup parameters.
 19. Restore backup parameters.
 20. Two room set-up (for use with dual DMX input).
 21. Onboard protocol manager (DMX input merge or back up).
 22. CD-2000 keypad lockout.
 23. Infrared print-out of the following programmed parameters:
 - a) System (vital system parameters)
 - b) Patch
 - c) Curves
 - d) Analog HTP assignments
 - e) Preset schedules
 - f) Preset fade times
 - g) Preset levels
 - h) All (a continuous printout of all the above)
 24. Diagnostic features:
 - a) Input data test
 - b) Dimmer test
 - c) Analog input test
 - d) Preset station test
 - e) Clock calibrate
 - f) Clear functions
 - g) System and Network status
 - h) Software Rev. and serial number display
- 2.10 The ECU module shall include an LED indicator for power supply and microprocessor status. The LED, when illuminated, shall indicate normal operation, and when flashing shall indicate a hardware fault. A power supply or power failure, shall cause the LED to extinguish.
- 2.11 The PSR module shall include three LED's for phase detect, and two LED's for data receive indication. Loss of accurate phase detect signal shall cause the corresponding LED to extinguish.
- 2.12 A reset push-button shall be included on the face of the module. Resetting the unit, whether by the reset button or power-up shall not affect any stored parameters or presets, and dimmer outputs shall automatically return to their former status without any noticeable change.
- 2.13 A "Panic" slide switch shall be included on the face of the unit. When "Panic" mode is selected, up to 96 pre-assigned dimmers shall be forced to full output regardless of their previous settings. The panic function shall not be dependent upon microprocessor operation. Withdrawing the ECU command module from the cabinet shall also initiate the panic function.
- 2.14 Multiple CD-2000's shall be capable of RS485 networking between the "Master" CD-2000 and the "Slave" CD-2000 units via the "CD-NET". It shall only be necessary to program the system "Master" with network wide information.
- 2.15 It shall be possible to "Lock" and "Unlock" the programming keypad of the CD-2000 ECU module in order to protect all programmed system data.
- 2.16 The CD-2000 shall incorporate fan control circuitry designed to allow for an additional five (5) minutes of air evacuation from the dimmer cabinet with loss of input control signal.
- 2.17 In the event of a dimmer "over temperature" signal, the CD-2000 will activate a flashing "OT" on all system JS-2809 control stations if equipped.

Specifications subject to change without notice. CD80® is a registered trademark of Strand Lighting.

Model	Description
CD-2000-A	Strand CD80® AMX racks
CD-2000-AE	Strand CD80® Advanced Electronics racks
CD-2000-SV	Strand CD80® Supervisor racks
CD-2000-RR	Strand CD80® 96 Channel rolling racks (2 x 48)



JOHNSON SYSTEMS INC.

"PROGRESSIVE ALTERNATIVES IN LIGHTING CONTROL"

1923 Highfield Crescent S.E.
 Calgary, Alberta, Canada T2G 5M1
 tel: 403.287.8003
 fax: 403.287.9003
 e-mail: info@johnsonsystems.com
 website: www.johnsonsystems.com

MANUFACTURER MEMBER

ESTA



ENTERTAINMENT SERVICES & TECHNOLOGY ASSOCIATION